




# FMAС(M)4000



• AR : 21°  
• RR : -17°~-12°

Обозначение	⊙	ØD	ØD <sub>2</sub>	Ød	a	b	E	F	Ød <sub>1</sub>	Ød <sub>2</sub>	ap	kg	Рис.
<b>FMAС(M) 4050HR</b>	3	50	49	22	10.4	6.3	20	40	11	18	6.5	0.4	1
<b>4063HR</b>	4	63	49	22	10.4	6.3	20	40	11	18	6.5	0.6	1
<b>4063HR-M</b>	5	63	49	22	10.4	6.3	20	40	11	18	6.5	0.6	1
<b>4063HR-H</b>	6	63	49	22	10.4	6.3	20	40	11	18	6.5	0.6	1
<b>4080HR</b>	5	80	57	25.4(27)	9.5(12.4)	6(7)	25(23)	50	14	20	6.5	1.1	1
<b>4080HR-M</b>	6	80	57	25.4(27)	9.5(12.4)	6(7)	25(23)	50	14	20	6.5	1.1	1
<b>4080HR-H</b>	8	80	57	25.4(27)	9.5(12.4)	6(7)	25(23)	50	18	20	6.5	1.1	1
<b>4100HR</b>	5	100	67	31.75(32)	12.7(14.4)	8(8)	33(25)	63(50)	18	26	6.5	2(1.6)	1
<b>4100HR-M</b>	7	100	67	31.75(32)	12.7(14.4)	8(8)	33(25)	63(50)	18	26	6.5	2(1.6)	1
<b>4100HR-H</b>	10	100	67	31.75(32)	12.7(14.4)	8(8)	33(25)	63(50)	18	26	6.5	2(1.6)	1
<b>4125HR</b>	6	125	87	38.1(40)	15.9(16.4)	10(9)	35(29)	63	22	32	6.5	3.1	1
<b>4125HR-M</b>	8	125	87	38.1(40)	15.9(16.4)	10(9)	35(29)	63	22	32	6.5	3.1	1
<b>4125HR-H</b>	12	125	87	38.1(40)	15.9(16.4)	10(9)	35(29)	63	22	32	6.5	3.1	1
<b>4160R</b>	7	160	107	50.8(40)	19.0(16.4)	11(9)	38(35)	63	-	-	6.5	4.8	2
<b>4160R-M</b>	10	160	107	50.8(40)	19.0(16.4)	11(9)	38(35)	63	-	-	6.5	4.8	2
<b>4160R-H</b>	16	160	107	50.8(40)	19.0(16.4)	11(9)	38(35)	63	-	-	6.5	4.8	2
<b>4200R</b>	8	200	130	47.625(60)	25.4(25.7)	14	38(32)	63	-	-	6.5	6.1	3
<b>4200R-M</b>	12	200	130	47.625(60)	25.4(25.7)	14	38(32)	63	-	-	6.5	6.1	3
<b>4200R-H</b>	18	200	130	47.625(60)	25.4(25.7)	14	38(32)	63	-	-	6.5	6.1	3

\* ( ) Метрическая система

## Применяемые СМП

	SEET-MF	SEET-MM	SEET-MA	SEXT-MF	SEXT-MM	SEXT-MR	SEEW	SEEW-W
Обозначение	NCM825 NCM835 NC5330 PC3500 PC3545 PC3530 PC6510 PC215K PD2000 CN2000 CN30 CN30 H01 G10 ST30A ST20	Тв. сплав с покрытием		Кермет		Тв. сплав		Стр.
SEET	14M4AGFN-MA	14M4AGSN-MF	14M4AGSN-MM	14M4AGSN-MF	14M4AGSN-MM	14M4AGSN-MR	14M4AGTN	E14 E15
SEXT	14M4AGSN-MF	14M4AGSN-MM	14M4AGSN-MR	14M4AGSN-MF	14M4AGSN-MM	14M4AGSN-MR	14M4AGFN-W	
SEEW	14M4AGTN	14M4AGFN-W	14M4AGSN-W	14M4AGSN-W	14M4AGTN-W	14M4AGTN-W	14M4AGTN-W	

## Применяемые оправки

Обозначение	Ød	Оправка с хвостиком BT
FMAС(M) 4050HR-□	22	BT□□-FMC22-□□
4063HR-□	25.4	BT□□-FMA25.4-□□
4080HR-□	27	BT□□-FMC27-□□
4100HR-□	31.75	BT□□-FMA31.75-□□
4125HR-□	32	BT□□-FMC32-□□
	38.1	BT□□-FMA38.1-□□
	40	BT□□-FMB40-□□
4160R-□	50.8	BT□□-FMA50.8-□□
	40	BT□□-FMB40-□□
4200R-□	47.625	BT□□-FMA47.625-□□
	60	BT□□-FMB60-□□

## Комплектующие



FTGA03512 SS42SAF SHXN0509F TW15S HW35L

Применяемые СМП смотреть на стр. E14, E15

Присоединительные размеры смотреть на стр. E277~E279

● : Наличие на складе

