



FMPC(M)3000-A

(Алюминиевый корпус)



• AR : 10°
• RR : -9°~-7.3°

(мм)

Обозначение		$\varnothing D$	$\varnothing D_2$	$\varnothing d$	a	b	E	F	$\varnothing d_1$	$\varnothing d_2$	ap		Рис.	
FMPC(M) 3063S-A		3	63	40	22	10.4	6.3	20	40	11.0	18	4	0.2	1
3080S-A		4	80	55	25.4(27)	9.5(12.4)	6(7)	25(22)	50	13.5	20	4	0.4	1
3100S-A		5	100	67	31.75(32)	12.7(14.4)	8(8)	32	50	-	45	4	0.6	2
3100S-25.4-A		5	100	67	25.4	9.5	6	25	50	-	38	4	0.7	2

• () Метрическая система


Применяемые СМП

	SDET-MF	SDET-MM	SDET-MA	SDXT-MF	SDXT-MM	SDXT-MA													
Обозначение	Тв. сплав с покрытием								Кермет			Тв. сплав				Стр.			
	NCM325	NCM335	NC5330	PC3500	PC5300	PC5400	PC3545	PC9530	PC6510	PD2000	CN2000	CN20	CN30	H01	G10	ST30A	ST20		
SDET 09M402R-MA										●				●				E13	
SDET 09M405R-MF																			E14
SDET 09M405R-MM																			
SDXT 09M405R-MF	●	●			●	●			●	●									
SDXT 09M405L-MF																			
SDXT 09M405R-MM	●	●		●	●	●			●	●									
SDXT 09M405L-MM																			
SDXT 09M405R-MA																			

Применяемые оправки

Обозначение	$\varnothing d$	Оправка с хвостовиком BT
FMPC(M) 3063S-□	22	BT□□-FMC22-□□
3080S-□	25.4	BT□□-FMA25.4-□□
3100S-□	27	BT□□-FMC27-□□
3100S-□	31.75	BT□□-FMA31.75-□□
3125S-□	32	BT□□-FMC32-□□
3125S-□	38.1	BT□□-FMA38.1-□□
3125S-□	40	BT□□-FMB / FMC40-□□

Комплектующие



3063S-A	FTGA03508	TW15S	HW30L	LFMP3R-A	DHA0624	CFMP3R14R1-A	PXMA0306
3080S-A ~ 3100S-A	FTGA03508	TW15S	HW30L	LFMP3R-A	DHA0624	CFMP3R-A	PXMA0306



Применяемые СМП E13, E14, E15



Присоединительные размеры смотреть на стр. E270~E272

● : Наличие на складе