


# AMC(M)1000S



(MM)

Обозначение		ØD	ØD <sub>2</sub>	Ød	Ød <sub>1</sub>	Ød <sub>2</sub>	a	b	E	F	ap	
<b>AMC(M) 1032HS</b>	8	32	30	16	9	14	8.4	5.6	19	40	5.6	0.15
<b>1040HS-16</b>	10	40	34	16	9	14	8.4	5.6	19	40	5.6	0.24
<b>1040HS-22</b>	10	40	34	22	11	18	10.4	6.3	21	40	5.6	0.24
<b>1050HS</b>	12	50	42	22	11	18	10.4	6.3	21	40	5.6	0.36
<b>1063HS</b>	14	63	49	22	11	18	10.4	6.3	21	40	5.6	0.61

## Применяемые СМП

APMT-MM

APMT-MF




Обозначение	Тв. сплав с покрытием									Кермет			Тв. сплав				Стр.	
	NCM325	NCM335	NC5330	PC3500	PC5300	PC3545	PC9530	PC6510	PC215K	PD2000	CN2000	CN20	CN30	H01	G10	ST30A		ST20
APMT 060202PDSR-MM			●	●	●	●												E05
0602PDSR-MM			●	●	●	●	●											
060208PDSR-MM			●	●	●	●												
060212R-MM			●	●	●													

## Применяемые оправки

Обозначение	Ød	Оправка с хвостовиком BT
AMC(M) 1032HS 1040HS-16 1040HS-22	16	BT □□-FMC16-□□
1050HS 1063HS	22	BT □□-FMC22-□□

## Комплектующие



FTKA01842

TW06S-A